

Solar System

YOBOLIFE



TECHNICAL PARAMETER

Model No.		Kits-9017	
DC box configuration		Working time after full charge	
Power Bank	LiFePO4 12.8V 160WH (3.2V 50400mAh)	LED lighting	15hours /30hours
DC Output	12V*5pcs	1 LED bulb	50 hours/100hours
USB Output	5V 2.4A/1.0A	2 LED bulbs	26 hours/52hours
LED light with 2 gears to adjust the brightness :High/low		3 LED bulbs	17 hours/34hours
Solar /AC adapter charge port*1pcs		4 LED bulbs	13hours/26hours
12V 120Wcigarette lighter		Full Charging time by solar panel	10-12 hours
Applications	tablet,DC12V TV (<32inch),DC 12V Fan/USB Fan.	Full Charging time by AC adapter	4-6 hours

whole package details		CBM&weight	
LED bulbs	12V5W*4 PCS (5M cable)	G.W	24.5KGS
Solar panel	16V28W*1pcs(1M cable)	QTY	4set/CTN
Adapter	16V 1A	CBM	0.086m ³
12V DC box *1pcs		Carton	48.5*43.5*41C
5 in 1 mobile phone charge cable*1M		20'GP	13000PCS
12VDC TV double ended DC Cable *1pcs*1.5M		40"HQ	3160PCS



115mm

260mm

180mm



480mm

340mm





LED switch

Handle

LED lighting
High/Low

Multifunction Solar Lighting System
Model: YOBOLIFE
Battery: LiFePO4 12.8V 1800mAh 10440mAh 3.2V 1
Input: 12V 10W 1.2A 12V 10W 1.2A 12V 10W 1.2A
Output: 12V 10W 1.2A 12V 10W 1.2A 12V 10W 1.2A
Power: 12V 10W 1.2A 12V 10W 1.2A 12V 10W 1.2A
Warning: Do not use the battery to charge more than
10V or use the battery to charge more than
10V. Please charge it in time after use.
Made in China